Ferrite Keys on home

RT-950 Pro

KEY	PRESS	HOLD
MENU	Quick settings	The full menu
BACK	Back one step	Home, from anywhere
Knob, ▲▼	Tune, or step channels	—
◀▶	Channel: zone. VFO: band	—
ABC	Next slot, A → B → C	Edit the slot
V/M	VFO or channels	The zone list
SIDE1	Monitor on or off	Monitor while held. With the knob: squelch
SIDE2	Scan start or stop	Frequency counter. With the knob: big steps
*	Mute or unmute the slot. Twice quickly: slot off	The quick menu
#	Help (or pause watch)	Lock or unlock the keys (then * all, 0 all but PTT)
Digits	Type a frequency or channel	A shortcut (below)
PTT A	Transmit on the active slot	—
PTT B	Transmit on slot B	—
PTT + SIDE2	1750 Hz tone burst	—

Ferrite Keys on home

RT-950 Pro

KEY	PRESS	HOLD
MENU	Quick settings	The full menu
BACK	Back one step	Home, from anywhere
Knob, ▲▼	Tune, or step channels	—
◀▶	Channel: zone. VFO: band	—
ABC	Next slot, A → B → C	Edit the slot
V/M	VFO or channels	The zone list
SIDE1	Monitor on or off	Monitor while held. With the knob: squelch
SIDE2	Scan start or stop	Frequency counter. With the knob: big steps
*	Mute or unmute the slot. Twice quickly: slot off	The quick menu
#	Help (or pause watch)	Lock or unlock the keys (then * all, 0 all but PTT)
Digits	Type a frequency or channel	A shortcut (below)
PTT A	Transmit on the active slot	—
PTT B	Transmit on slot B	—
PTT + SIDE2	1750 Hz tone burst	—

Ferrite Shortcuts

RT-950 Pro

HOLD A DIGIT

0	Home channel
1	Band scope
2	TX power: low, mid, high
3	Squelch
4	Watch on or off
5	Tone picker
6	Next step size (VFO)
7	Shift: simplex, +, –
8	Offset amount
9	Save the VFO as a channel, or copy a channel to the VFO

On a channel, hold 7 and hold 8 open the channel's editor.

QUICK SETTINGS · MENU

1	Squelch
2	TX power
3	Mode
4	Tones
5	Offset
6	Step (VFO)
7	Watch
8	Save or edit the channel
9	Battery Save
0	The full menu

QUICK MENU · hold *

Knob	Brightness
PTT A	Reverse on or off
PTT B	Night red on or off
SIDE1	GPS: Off, Auto or On
SIDE2	Bluetooth on or off

IN LISTS

▲▼	Move
Knob, ◀▶	Change the value (it applies at once)
OK	Open, or a bigger editor
#	Back to the default
*	Undo, for 5 seconds
BACK	Back one level
PTT	Keep the change, go home and transmit

Typing text (names, callsigns, messages): press a digit several times for its letters. * is a space and # changes upper case, lower case and symbols, as the keys are marked. 1 has . - / @ before its digit; in a callsign only - (your own callsign: - and /). In a message, # also reaches T9, typing word by word. BACK deletes.

Ferrite Shortcuts

RT-950 Pro

HOLD A DIGIT

0	Home channel
1	Band scope
2	TX power: low, mid, high
3	Squelch
4	Watch on or off
5	Tone picker
6	Next step size (VFO)
7	Shift: simplex, +, –
8	Offset amount
9	Save the VFO as a channel, or copy a channel to the VFO

On a channel, hold 7 and hold 8 open the channel's editor.

QUICK SETTINGS · MENU

1	Squelch
2	TX power
3	Mode
4	Tones
5	Offset
6	Step (VFO)
7	Watch
8	Save or edit the channel
9	Battery Save
0	The full menu

QUICK MENU · hold *

Knob	Brightness
PTT A	Reverse on or off
PTT B	Night red on or off
SIDE1	GPS: Off, Auto or On
SIDE2	Bluetooth on or off

IN LISTS

▲▼	Move
Knob, ◀▶	Change the value (it applies at once)
OK	Open, or a bigger editor
#	Back to the default
*	Undo, for 5 seconds
BACK	Back one level
PTT	Keep the change, go home and transmit

Typing text (names, callsigns, messages): press a digit several times for its letters. * is a space and # changes upper case, lower case and symbols, as the keys are marked. 1 has . - / @ before its digit; in a callsign only - (your own callsign: - and /). In a message, # also reaches T9, typing word by word. BACK deletes.